

Illustrative render generated from published specifications

AWT 40A
3300mAh



Live page & updates

AWT · released 2018

- 18650
- LMO
- MOOCH-TESTED · 40 A

3,300 mAh CAPACITY	40 A MOOCH CONTINUOUS	3.6 V NOMINAL · 2.75 – 4.2 V	11.88 Wh ENERGY
--	---	--	---------------------------------------

REFERENCE ONLY — NOT AN OFFICIAL DOCUMENT

This information is gathered from multiple sources, including manufacturer datasheets, independent third-party testing, and community contributions. Cell specifications vary between production batches and change over time, and no figure here is guaranteed to be correct or current. **Always consult the manufacturer's spec sheet directly.** Use this sheet for reference only — never as the sole basis for a safety-critical decision about charging, discharging, or assembling cells. The cell image is an illustrative render generated from published specifications, not a photograph.

CAPACITY AMONG 18650S #21 of 279 Lowest in database Highest Top tier for both capacity and discharge. One of the best all-around 18650 cells.	VOLTAGE OPERATING WINDOW 1.45 V usable Cutoff 2.75 V Nominal 3.6 V Max 4.2 V Below nominal the cell sags fast under load; above it, the last of the capacity fills slowly on the constant-voltage taper.
--	--

APPLICATION SUITABILITY

Rule-of-thumb ratings from this cell's capacity and continuous discharge. Check your own load before committing.

Powerwalls	High capacity means more stored energy per cell. Fewer cells needed for a given kWh target.
Ebike packs	Good balance of capacity for range and discharge for hills. Works well in most ebike packs.
Car audio	Enough discharge to handle amplifier bursts without voltage sag.
High-drain vaping	Above the 25A Moolch CDR threshold. Suitable for regulated and mechanical mods.
Flashlights	High capacity means long runtime. Great for everyday carry and extended use.
Power tools	Sufficient discharge and capacity for most power tool packs.

IDENTITY		ELECTRICAL	
Manufacturer	AWT	Rated capacity	3,300 mAh
Model	40A 3300mAh	Nominal voltage	3.6 V
Format	18650	Max charge voltage	4.2 V
Chemistry	LMO	Discharge cutoff	2.75 V
Year released	2018	Energy	11.88 Wh
Wrap colour	Patterned	Internal resistance	30.8 mΩ
Terminal	Flat top	Max continuous discharge	40 A (mooch)
Protection	Unprotected	Discharge C-rate	12.1C
ENERGY & POWER DENSITY		Cycle life	500 cycles
Energy	11.88 Wh		
Capacity ranking	#21 of 279 18650s		

C-RATE CONVERSION · 3,300 MAH

C-RATE	CURRENT	THEORETICAL RUNTIME
0.2C	0.66 A	5h 00m
0.5C	1.65 A	2h 00m
1C	3.3 A	1h 00m
2C	6.6 A	30m
3C	9.9 A	20m
5C	16.5 A	12m
8C	26.4 A	7m 30s
10C	33 A	6m

Highlighted row is closest to the rated 40 A continuous discharge.

CHARGING

RATE	CURRENT	ESTIMATED TIME TO FULL
0.5C	1,650 mA	~2h 00m
1C	3,300 mA	~1h 00m

Constant-current phase only. Real charge time runs longer because of the constant-voltage taper at the end.

SERIES PACK CONFIGURATIONS

Voltages calculated from this cell's own nominal and maximum charge voltage. The 3P columns show one common parallel count as a worked example — scale the parallel group to the capacity you need.

SERIES	NOMINAL	FULLY CHARGED	CELLS AT 3P	CAPACITY	ENERGY
3S	10.8 V	12.6 V	9	9.9 Ah	107 Wh
7S	25.2 V	29.4 V	21	9.9 Ah	249 Wh
10S	36 V	42 V	30	9.9 Ah	356 Wh
13S	46.8 V	54.6 V	39	9.9 Ah	463 Wh
14S	50.4 V	58.8 V	42	9.9 Ah	499 Wh

EXAMPLE PACKS

7S2P 24V ebike / small pack 14 cells · 25.2 V 6,600 mAh · 166 Wh 80 A max	13S4P 48V ebike standard 52 cells · 46.8 V 13,200 mAh · 618 Wh 160 A max	16S4P DIY powerwall 64 cells · 57.6 V 13,200 mAh · 760 Wh 160 A max	4S6P Power tool replacement 24 cells · 14.4 V 19,800 mAh · 285 Wh 240 A max
--	---	--	--

SIMILAR CELLS

Same format and chemistry, within ± 500 mAh.

CELL	MAH	CONTINUOUS	WH	WEIGHT	WH/KG
AWT 40A 3300mAh (this cell)	3,300	40 A	11.88	—	—
Efest EFEST 35A 2900mAh	2,900	35 A	10.4	—	—
Efest 18650 2800mAh 35A	2,800	35 A	10.1	46 g	219

HANDLING & SAFETY

- Never charge above 4.2V or discharge below 2.75V.
- Store cells at around 3.6-3.8V (roughly 40-60% charge) for long-term storage.
- Don't mix cells with different capacities, chemistries, or states of charge in a pack.
- Inspect wraps before use. A torn wrap can cause a short circuit.
- Always use a BMS or balance charger appropriate for your pack configuration.
- Keep cells away from metal objects, keys, and coins. A short across the terminals can cause fire.

SOURCES & FURTHER READING

Cell Savors page	cellsaviors.com/cell-database/awt-40a-3300mah
Independent test (Mooch)	https://www.e-cigarette-forum.com/threads/bench-test-results-a...
Full cell database	cellsaviors.com/cell-database