Illustrative render generated from published specifications

Efest 30EF

Efest

18650 · NMC · MOOCH-TESTED · 15 A

Live page & updates

3,000 mAh	15 A	3.6 V	10.8 Wh
CAPACITY	MOOCH CONTINUOUS	NOMINAL · 2.5 – 4.2 V	ENERGY

REFERENCE ONLY — NOT AN OFFICIAL DOCUMENT

This information is gathered from multiple sources, including manufacturer datasheets, independent third-party testing, and community contributions. Cell specifications vary between production batches and change over time, and no figure here is guaranteed to be correct or current. **Always consult the manufacturer's spec sheet directly.** Use this sheet for reference only — never as the sole basis for a safety-critical decision about charging, discharging, or assembling cells. The cell image is an illustrative render generated from published specifications, not a photograph.

CAPACITY AMONG 18650S

#37 of 279

Lowest in database — Highest

More capacity than 87% of 18650 cells in our database. One of the higher-capacity options.

VOLTAGE OPERATING WINDOW

1.7 V usable

Cutoff 2.5 V — Nominal 3.6 V — Max 4.2 V

Below nominal the cell sags fast under load; above it, the last of the capacity fills slowly on the constant-voltage taper.

APPLICATION SUITABILITY

Rule-of-thumb ratings from this cell's capacity and continuous discharge. Check your own load before committing.

Powerwalls	High capacity means more stored energy per cell. Fewer cells needed for a given kWh target.
Ebike packs	Good balance of capacity for range and discharge for hills. Works well in most ebike packs.
Car audio	Might work for smaller setups. Check your amp's peak current draw.
High-drain vaping	Usable in regulated mods at moderate wattage. Not recommended for mechanical mods.
Flashlights	High capacity means long runtime. Great for everyday carry and extended use.
Power tools	Sufficient discharge and capacity for most power tool packs.

IDENTITY

Manufacturer	**Efest**
Model	**30EF**
Format	**18650**
Chemistry	**NMC**
Wrap colour	**Pink**
Terminal	**Flat top**
Protection	**Unprotected**

ELECTRICAL

Rated capacity	**3,000 mAh**
Nominal voltage	**3.6 V**
Max charge voltage	**4.2 V**
Discharge cutoff	**2.5 V**
Energy	**10.8 Wh**
Max continuous discharge	**15 A (mooch)**
Discharge C-rate	**5C**

ENERGY & POWER DENSITY

Energy	**10.8 Wh**
Capacity ranking	**#37 of 279 18650s**

C-RATE CONVERSION · 3,000 MAH

C-RATE	CURRENT	THEORETICAL RUNTIME
0.2C	0.6 A	5h 00m
0.5C	1.5 A	2h 00m
1C	3 A	1h 00m
2C	6 A	30m
3C	9 A	20m
5C	**15 A**	**12m**

Highlighted row is closest to the rated 15 A continuous discharge.

CHARGING

RATE	CURRENT	ESTIMATED TIME TO FULL
0.5C	1,500 mA	~2h 00m
1C	3,000 mA	~1h 00m

Constant-current phase only. Real charge time runs longer because of the constant-voltage taper at the end.

SERIES PACK CONFIGURATIONS

Voltages calculated from this cell's own nominal and maximum charge voltage. The 3P columns show one common parallel count as a worked example — scale the parallel group to the capacity you need.

SERIES	NOMINAL	FULLY CHARGED	CELLS AT 3P	CAPACITY	ENERGY
3S	10.8 V	12.6 V	9	9 Ah	97 Wh
7S	25.2 V	29.4 V	21	9 Ah	227 Wh
10S	36 V	42 V	30	9 Ah	324 Wh
13S	46.8 V	54.6 V	39	9 Ah	421 Wh
14S	50.4 V	58.8 V	42	9 Ah	454 Wh

EXAMPLE PACKS

7S2P

24V ebike / small pack

14 cells · 25.2 V

6,000 mAh · 151 Wh

30 A max

13S4P

48V ebike standard

52 cells · 46.8 V

12,000 mAh · 562 Wh

60 A max

16S4P

DIY powerwall

64 cells · 57.6 V

12,000 mAh · 691 Wh

60 A max

4S6P

Power tool replacement

24 cells · 14.4 V

18,000 mAh · 259 Wh

90 A max

SIMILAR CELLS

Same format and chemistry, within ±500 mAh.

CELL	MAH	CONTINUOUS	WH	WEIGHT	WH/KG
Efest 30EF (this cell)	**3,000**	**15 A**	**10.8**	**—**	**—**
LG LGEBMJ11865	3,500	10 A	12.7	49 g	260
LG LGDBMJ11865	3,500	10 A	12.7	49 g	259
AWT AWT 35A 3500mAh	3,500	35 A	12.6	50 g	252
Epoch PROTECTED	3,500	8 A	12.6	49.1 g	257
EVE INR18650-35V	3,500	10 A	12.6	47 g	268

HANDLING & SAFETY

- Never charge above 4.2V or discharge below 2.5V.
- Store cells at around 3.6-3.8V (roughly 40-60% charge) for long-term storage.
- Don't mix cells with different capacities, chemistries, or states of charge in a pack.
- Inspect wraps before use. A torn wrap can cause a short circuit.
- Always use a BMS or balance charger appropriate for your pack configuration.
- Keep cells away from metal objects, keys, and coins. A short across the terminals can cause fire.

SOURCES & FURTHER READING

Cell Saviors page	cellsaviors.com/cell-database/efest-30ef
Independent test (Mooch)	https://www.e-cigarette-forum.com/threads/bench-test-results-e...
Full cell database	cellsaviors.com/cell-database